

## Z-100 Automatic Antenna Tuner



The Z-100 is the definitive low cost automatic antenna tuner! It has been designed from the ground up to provide the power handling you asked for, in a small, lightweight package that is perfect for portable as well as sitting on your desk in your shack!

The Z-100 will tune with 0.1 to 125 watts (50 watts on 6 meters), making it an excellent choice for almost any radio or operating style. Backpackers and QRP operators will appreciate the latching relays. Power can be removed from the tuner once you have tuned. Additionally, when the tuner is not tuning, it draws nearly zero amps.

Additionally, the Z-100 features 200 fast memories which will decrease tuning time up to 95%!

This automatic antenna tuner will interface to many radios for added convenience. Our optional interfaces integrate the tuner to the radio so you can take advantage of radio faceplate "tune buttons" (if so equipped) or tuner signaled tuning. Please consult your radio manual for details on using it with an automatic antenna tuner. Interfaces are available for certain Icom, Alinco, Yaesu, and Kenwood radios



Simple operation is the key to the Z-100. Provide a continuous carrier, then press and hold the tune button for 1 second. The Z-100 tunes. The red LED indicates tuner activity and the green LED indicates an SWR of 1.0 to 1.5 (steady Green LED) and 1.5 to 2.0 (blinking Green LED). If your antenna is already resonant, place the tuner in bypass. Pressing and releasing the tune button quickly will bypass the tuner, taking all tuning components out of line.

Operating range is 1.8 to 54 MHz and will tune a 10:1 SWR (3:1 on 6 meters) down to 1.5:1 or less. It will tune almost any coax fed antenna including dipoles, beams, and verticals. Add any 4:1 Balun to use ladder line or to tune long wire or Zepp antennas.

Please compare the price of the Z-100 to other brand auto and manual tuners... enough said!



## Specifications

- Microprocessor controlled
- High efficiency switched "L" tuning network
- LED indicators for Status and SWR.
- 200 fast memories
- Optional Icom, Alinco, Yaesu, and Kenwood interface
- Optimized, low power consumption tuning algorithm
- Tuning time: 0.5 to 6 seconds, 3.0 average
- Current consumption:
  - Idle - Nearly zero amps.
  - Tuning - 300 mA max
- Voltage requirements: 7 to 18 volts (user supplies power source)
- 1.8 to 54.0 MHz coverage
- Tunes 6 to 800 ohm loads, 10:1 SWR (3:1 SWR on 6 meters)
- Power range: 0.1 to 125 watts (50 watts on 6 meters)
- For Dipoles, Verticals, Vees, Beams and Coax Fed Antennas
- Enclosure sizes: 5.5" x 5.25" x 1.5"
- Weight: 14 oz

Autoryzowany Przedstawiciel LGD w Polsce:


**INRADIO**  
**ABEL & PRO-FIT Centrum Radiokomunikacji**  
 ul. Puzkina 80 92-516 Łódź Poland  
 tel. (+42) 649 28 28 fax: (+42) 677 04 71  
 e-mail: biuro@inRADIO.pl  
 internet: www.inRADIO.pl